



SOLVIMUS

METERING SOLUTIONS

DATA SHEET MBUS-PU3

Version 1

Page 1/2

1. Product

MBUS-PU3, Art. No. 500358



2. Application

Level converter for the direct connection of meters to a meter data management system (meter readout system) via USB

3. Interfaces

M-Bus

Compliant to EN 13757-2 (all M-Bus meters are compatible), max. number of unit loads (UL): 3, baud rate: max. 9600 bps, spring terminal

USB

USB connector type A

4. LED indicators

Status LEDs signalling sending and receiving on the M-Bus as well as power supply

5. General properties

- Dimensions: 19 x 12 x 80 mm (W x H x D)
- Installation: directly on PC or mobile device
- Mass: 15 g

- Requires an appropriate USB COM port driver (e. g. CP210x Universal Windows Driver) in the host system.
- An external software (not included) is required to access the data of the M-Bus participants.

6. Power supply

- 4.75..5.25 VDC, USB connector type A, peak inrush-current <500 mA
- Power consumption: <0.1 W (idle state), max. 0.5 W

7. Environmental conditions

- Operation: 0..50 °C (daily average); -20..70 °C (short-time)
- Transport and storage: -20..70 °C
- Air humidity: 0..95 %, non-condensing

8. Conformity and safety

- 2014/30/EU EMV Directive
- 2014/35/EU Low Voltage Directive
- 2011/65/EU RoHS Directive (incl. amendment 2015/863)
- Overvoltage protection (transient)
- Degree of protection IP30 (IEC 60529)

9. Scope of delivery

- MBUS-PU3
- Quick Start Guide (print, in the packaging)
- Individual packaging with solvimus logo
- Dimensions: 115 x 29 x 54 mm (W x H x D)

10. Contact

solvimus GmbH
Ratsteichstr. 5
98693 Ilmenau
Germany
Phone: +49 3677 7613060
E-Mail: info@solvimus.de
www.solvimus.de



SOLVIMUS

METERING SOLUTIONS

DATA SHEET MBUS-PU3

Version 1

Page 2/2

Sales:

Phone: +49 3677 7613066

E-Mail: sales@solvimus.de

Support:

Phone: +49 3677 7613065

E-Mail: support@solvimus.de

Further contacts can be found on our website at:
<https://www.solvimus.de/en/company/solvimus/>

A comprehensive description of the device is provided in the manual that can be downloaded free of charge and without registration from our homepage:

<https://www.solvimus.de/en/products/downloads-2/>.

Our Quick Start Guide is also available upon request.

The solvimus GmbH works according to the principle of continuous improvement. The information given in this document is subject to change without prior notice and is provided without assertion, warranty or guarantee, including as to accuracy, completeness or fitness for a particular purpose. The statements in this document are not to be construed as a guarantee or assertion. This document is protected under copyright law.

